



# NG-610

## Conventional Fire Detection & Extinguishing Panel

NG-610 Conventional Fire Detection and Extinguishing Panel offers a creatively designed and aesthetically pleasing solution to satisfy the growing world demand for dependable Fire Suppression Systems.

NG-610 is designed and manufactured to comply with EN 54-2, 54-4 and EN 12094-1. The outstanding programmable features included in this panel are best suited to be installed in expensive housing areas and in general in all areas where loss of equipment can partially or totally disrupt the proper functioning of a business.

Operation is extremely intuitive, offering simple control and one-button disablement facilities, as well as the one man test mode which provides simple and efficient testing of the system.

Advanced configuration solutions include the following: programmable pre-release and extinguishing times, electrovalve and flow switch status indications, manual and abort remote activation. There are 3 normal fire detection zones. All inputs are fully monitored for both Fire, Activation and Fault Conditions.

## ► Key Features

- 3 Fire Detection Zones.
- Up to 32 conventional smoke and/or heat detectors per Zone
- Active End of Line monitoring
- Programmable Pre-Release and Extinguishing times
- Remote Manual Activation and Remote Abort Input
- Electrovalve and Pressure Switch Status Indication
- One man test
- Supervised auxiliary 24 volt supply output
- 2 Supervised/ monitored sounder circuits
- 2 Remote inputs used for activation of Evacuation and Reset
- 2 Relay outputs fire and fault with status indication
- Fully EN 54-2, EN54-4 and EN 12094-1 compliant

### Specifications

<b>SUPPLY SPECIFICATION</b>	
PRIMARY SUPPLY VOLTAGE- IN	230 +10% -15% V AC
PRIMARY SUPPLY VOLTAGE- OUT	28.5 V DC nominal
PRIMARY SUPPLY CURRENT-OUT	1.7 A @ 28.5 V DC nominal (max.)
SECONDARY SUPPLY VOLTAGE	21.0 min. - 27.2 max. V DC - BAT charger o/p 28 V DC
SECONDARY SUPPLY CURRENT OUTPUT	1.85 Amp Maximum @ 20°C
INTERNAL BATTERY CAPACITY - MAXIMUM	2 x 12V x 7Ah Sealed VRLA Lead Acid Batteries
MAINS FUSE	4 A -250 V Slow Blow - 20 mm
BATTERY FUSE	1.85 Amp - Resettable
<b>FIRE DETECTION CIRCUIT SPECIFICATION</b>	
NUMBER OF FIRE CIRCUITS	3
ZONE CURRENT - QUIESCENT/ ALARM	4 mA / 60 mA - Maximum
MAX. CABLE RESISTANCE / CAPACITANCE	40 Ohms / 0.470 uF
END OF LINE MONITORING	Active EOL - Capacitor
BS5839 DETECTOR REMOVAL COMPLIANT	YES provided diodes are fitted to detector base
DEVICES PER ZONE	32 Maximum - EN54 pt.2
ALARM RESISTANCE VALUE	270 - 1000 Ohms
<b>SOUNDER CIRCUIT SPECIFICATION</b>	
CURRENT OUTPUT	2 - 300mA max. current drive per circuit - fully monitored
VOLTAGE OUTPUT	27.5 V DC Nominal
END OF LINE RESISTOR	10 K Ohms - 1/4 Watt
<b>AUXILIARY OUTPUTS SPECIFICATION</b>	
AUXILIARY RELAY OUTPUT	1 Fire (COM-NC-NO) - 1 Fault (COM-NC) non-supervised
RELAY CONTACT RATING	50 V DC - 1 Amp resistive loads
<b>REMOTE INPUT SPECIFICATION</b>	
FULLY MONITORED INPUTS	Remote Activation, Remote Abort, Electrovalve Status, Flow Switch Status
EVACUATION and RESET	Non-Latching - Voltage free contact
<b>MECHANICAL &amp; OPERATING SPEC.</b>	
MAX. HUMIDITY	95% RH Non-Condensing
OPERATING TEMPERATURE	-5°C to 50°C
WEIGHT	1.7 Kg - 7 Kg (inc. 2 x 7 AH 12 V bat.)
DIMENSIONS	272 (W) x 404 (H) x 107 (D) mm